




For wireless dimming compatible with Amazon Echo Plus, Philips Hue and Homee see page 241.

STRANGE

CEILING RECESSED



1.0 LED

LED 7/10W | 350/500mA | 18Vf
COB 3-step | excl. power supply
aluminium powder coated
1800-2850K 16V

0.43kg IP20 36°

35°/35° 355° 95

CODE

131161W_
131161B_

LIGHT COLOUR LUMEN | CRI CODE

2700K	510/680	>90	3
3000K	550/740	>90	5
1800-2850K	330/450	>95	9

ALWAYS USE

plastic plasterkit 86x86 10 or 13

CODE

90017122
90017116

aluminium plasterkit 86x86 8-32

CODE


90017120

power supply | 500mA

CODE

10W	90214405
15W dim	90224501
20W DALI	90244602

350mA power supplies on page 694



2.0 LED

2x LED 7/10W | 350/500mA | 18Vf
COB 3-step | excl. power supply
aluminium powder coated
1800-2850K 16V

0.74kg IP20 36°

35°/35° 355° 95

CODE

131261W_
131261B_

LIGHT COLOUR LUMEN | CRI CODE

2700K	2x510/680	>90	3
3000K	2x550/740	>90	5
1800-2850K	2x330/450	>95	9

ALWAYS USE

plastic plasterkit 86x156 10 or 13

CODE

90017123
90017117

aluminium plasterkit 86x156 8-32

CODE


90017121

power supply | 500mA

CODE

10W	90214405
15W dim	90224501
20W DALI	90244602

350mA power supplies on page 694



1.0 PAR16

PAR16 max. 12W | GU10
100-240VAC | 50-60Hz
aluminium powder coated

0.41kg IP20 36°

35°/35° 355° 120

CODE

131120W0
131120B0

ALWAYS USE

plastic plasterkit 86x86 10 or 13

CODE

90017122
90017116

aluminium plasterkit 86x86 8-32

CODE

90017120


OPTIONAL

PAR16 LED GU10 7W | phase-cut dim

CODE

2700K	901228W2
3000K	901228W4
1800-2850K	901229S9

more lamps and specs on page 701



2.0 PAR16

2x PAR16 max. 12W | GU10
100-240VAC | 50-60Hz
aluminium powder coated

0.70kg IP20 36°

35°/35° 355° 120

CODE

131220W0
131220B0

ALWAYS USE

plastic plasterkit 86x156 10 or 13

CODE

90017123
90017117

aluminium plasterkit 86x156 8-32

CODE

90017121

OPTIONAL

PAR16 LED GU10 7W | phase-cut dim

CODE

2700K	901228W2
3000K	901228W4
1800-2850K	901229S9

more lamps and specs on page 701