

# SNEAK TRIM 1.0

01-Jul.-2017

## 1.0 LED

LED 7/10W | 350-500mA | 18Vf | COB 3-step | excl. power supply

CE IP20  $\phi$ 0.3m  $\Delta$  32°  $\curvearrowright$  35°/35°  $\downarrow$  355°

white texture	155351W_
black texture	155351B_


### LIGHT COLOUR

2700K   >90CRI   335-470lm	3
3000K   >90CRI   375-510lm	5
1800-2850K   >95CRI   255-350lm	9


### ALWAYS USE

for power supplies see our catalogue


side view




bottom view




①



②



④



## DIMENSIONS



## MOUNTING INSTRUCTION


① Make a hole in the ceiling according to the prescribed dimensions.

② Insert the fixture in the hole

## ③ POWER CONNECTION

SERIAL CONNECTION - for LED

**Always use POWER SUPPLY according to the specifications of the LED-module**



④ Place the LED-module in the fixture.



**WEVER & DUCRÉ**  
LIGHTING

[www.weverducre.com](http://www.weverducre.com)

Wever & Ducre bvba Kwadestraat 153 bus 2.1 8800 Roeselare

**INSTALLATION  
INSTRUCTIONS**